

Entrance 2

Auxiliary pedestal Keypad Unit




Master Keypad Unit




All devices are connected to a master unit which has a built in transmitter.

Entrance 1



- Can have a mix of keypads & card reader units in one set up.
- DDA LEDS on each auxiliary unit indicates correct or incorrect code/card used.
- Relay on every auxiliary unit that can be set via a dip switch.
- Keypad tones/ confirmation sound can be adjusted on auxiliary units.
- Units are wired via 5 cores of cat 5 cable.




Entrance 3



card Reader Unit

Auxiliary pedestal card reader & Keypad Unit





Technical Details	
Power	24v d.c
Current	300mA/2A Peak 100mA Per Auxiliary Unit
Weather Rating	IP55
Relay Type	2 x N/C & N/O Contacts
Total Permanent Keypad Codes	250
Total Permanent Prox Cards	250
Time Restricted Codes/Cards (Relay 1 only)	250
Temporary Codes/Cards (Relay 1 only)	50







Master Units: Keypads, Prox readers & built in transmitter.



KEY-MST-PED-KP-PX-US

Master unit with keypad & card reader.




KEY-MST-PED-KP-US

Master unit with keypad.



KEY-MST-PED-PX-US

Master unit with card reader.



Auxiliary Pedestal Keypads & Prox readers.



KEY-AUX-PED-KP-PX-US

Aux pedestal unit with keypad & card reader.




KEY-AUX-PED-KP-US

Aux pedestal unit with keypad.



KEY-AUX-PED-PX-US

Aux pedestal unit with card reader.



Auxiliary Keypads & Prox readers.



KEY-AUX-MOD-KP-PX-US

Aux unit with keypad & card reader.



KEY-AUX-MOD-KP-US

Aux unit with keypad.



KEY-AUX-MOD-PX-US

Aux unit with card reader.

